

2.15 5G band TX0 Power (78h~9Ah)

To prevent reading from EMPTY E2PROM, driver treats these “Channel xx Tx Power” value 0 and any value > =0x2C as invalid..

5GHz TX0 power setting register

Offset	b15 ~b8	b7 ~ b0
78h	Channel 38 TX0 power	Channel 36 TX0 power
7Ah	Channel 44 TX0 power	Channel 40/42 TX0 power
7Ch	Channel 48/50 TX0 power	Channel 46 TX0 power
7Eh	Channel 54 TX0 power	Channel 52 TX0 power
80h	Channel 60 TX0 power	Channel 56/58 TX0 power
82h	Channel 64 TX0 power	Channel 62 TX0 power
84h	Channel 102 TX0 power	Channel 100 TX0 power
86h	Channel 108 TX0 power	Channel 104/106 TX0 power
88h	Channel 112/114 TX0 power	Channel 110 TX0 power
8Ah	Channel 118 TX0 power	Channel 116 TX0 power
8Ch	Channel 124 TX0 power	Channel 120/122 TX0 power
8Eh	Channel 128/130 TX0 power	Channel 126 TX0 power
90h	Channel 134 TX0 power	Channel 132 TX0 power
92h	Channel 140/142/144 TX0 power	Channel 136/138 TX0 power
94h	Channel 151 TX0 power	Channel 146/149 TX0 power
96h	Channel 157 TX0 power	Channel 153/155 TX0 power
98h	Channel 161/163 TX0 power	Channel 159 TX0 power
9Ah	Reserved	Channel 165 TX0 power